

## Formula

Type: Methane Sensor METS

Serial number: **G60-E275**

$$c = \exp \left[ 1,978 * \ln \left\{ \left( 0,188 + 1,122 * \exp \frac{-V_t}{1,180} \right) * \left( \frac{1}{0,01 + 1,01 * V_{CH_4}} - \frac{1}{-2,906 + 11,694 * \exp \frac{-V_t}{1,552}} \right) \right\} \right]$$

$$t = (V_t * 22,79) - 3,86$$

O<sub>2</sub> correction:

$$c_{CH_4}(corr) = \left( -0,316 + 0,341 * \exp \frac{c_{O_2}}{74,800} \right) * c_{CH_4}$$

$c_{CH_4}$  = methane concentration [ $\mu\text{mol/l}$ ]

$t$  = gas temperature [ $^{\circ}\text{C}$ ]

$V_{CH_4}$  = methane voltage [V]

$V_t$  = temperature voltage [V]

$c_{O_2}$  = O<sub>2</sub> concentration [%]

Methane range: 10 nmol/l - 1  $\mu\text{mol/l}$

Temperature range: 10 – 30  $^{\circ}\text{C}$

Calibrator : J.G. ....

Date : .....